

Motor horsepower/standard kilowatt equivalent	Nominal full load efficiency					
	Open motors (number of poles)			Enclosed motors (number of poles)		
	6	4	2	6	4	2
5/3.7 .....	87.5	87.5	85.5	87.5	87.5	87.5
7.5/5.5 .....	88.5	88.5	87.5	89.5	89.5	88.5
10/7.5 .....	90.2	89.5	88.5	89.5	89.5	89.5
15/11 .....	90.2	91.0	89.5	90.2	91.0	90.2
20/15 .....	91.0	91.0	90.2	90.2	91.0	90.2
25/18.5 .....	91.7	91.7	91.0	91.7	92.4	91.0
30/22 .....	92.4	92.4	91.0	91.7	92.4	91.0
40/30 .....	93.0	93.0	91.7	93.0	93.0	91.7
50/37 .....	93.0	93.0	92.4	93.0	93.0	92.4
60/45 .....	93.6	93.6	93.0	93.6	93.6	93.0
75/55 .....	93.6	94.1	93.0	93.6	94.1	93.0
100/75 .....	94.1	94.1	93.0	94.1	94.5	93.6
125/90 .....	94.1	94.5	93.6	94.1	94.5	94.5
150/110 .....	94.5	95.0	93.6	95.0	95.0	94.5
200/150 .....	94.5	95.0	94.5	95.0	95.0	95.0

(b) For purposes of determining the required minimum nominal full load efficiency of an electric motor that has a horsepower or kilowatt rating between two horsepower or kilowattages listed consecutively in paragraph (a) of this section, each such motor shall be deemed to have a horsepower or kilowatt rating that is listed in paragraph (a) of this section. The rating that the motor is deemed to have shall be determined as follows:

(1) A horsepower at or above the midpoint between the two consecutive horsepower shall be rounded up to the higher of the two horsepower;

(2) A horsepower below the midpoint between the two consecutive horsepower shall be rounded down to the lower of the two horsepower, or

(3) A kilowatt rating shall be directly converted from kilowatts to horsepower using the formula, 1 kilowatt = (1/0.746) horsepower, without calculating beyond three significant decimal places, and the resulting horsepower shall be rounded in accordance with paragraphs (b)(1) or (b)(2) of this section, whichever applies.

(c) This section does not apply to definite purpose motors, special purpose motors, and those motors exempted by the Secretary.

**§ 431.26 Preemption of State regulations.**

Any State regulation providing for any energy conservation standard, or other requirement with respect to the energy efficiency or energy use, of an electric motor that is not identical to

a Federal standard in effect under this subpart is preempted by that standard, except as provided for in Section 345(a) and 327(b) and (c) of the Act.

**LABELING**

**§ 431.30 Applicability of labeling requirements.**

The labeling rules in § 431.31, established pursuant to Section 344 of EPCA, 42 U.S.C. 6315, apply only to electric motors manufactured after October 5, 2000.

**§ 431.31 Labeling requirements.**

(a) *Electric motor nameplate*—(1) *Required information.* The permanent nameplate of an electric motor for which standards are prescribed in § 431.25 must be marked clearly with the following information:

(i) The motor's nominal full load efficiency (as of the date of manufacture), derived from the motor's average full load efficiency as determined pursuant to this subpart; and

(ii) A Compliance Certification number ("CC number") supplied by DOE to the manufacturer or private labeler, pursuant to § 431.36(f), and applicable to that motor. Such CC number must be on the nameplate of a motor beginning 90 days after either:

(A) The manufacturer or private labeler has received the number upon submitting a Compliance Certification covering that motor, or